ARVOX

Mixer Amplifier

MP3 6-Zone Mixer Amplifier

(6-Zone, Mp3/FM, Bluetooth, VC for each zone)

RS-6S120 (120W)

RS-6S240 (240W)

RS-6S360 (360W)

RS-6S500 (500W)

RS-6S650 (650W)



Descriptions

* It adopts advanced and efficient power amplification circuit;
* With player and LCD screen, wireless Bluetooth playback, radio and USB playback;
* With 3-channel microphone input, 2-channel line input and 1-channel auxiliary output, and 6-channel partition selection output;
* The output volume of each partition can be adjusted independently;
* Each input volume can be controlled independently, with high and low volume adjustment;
* Microphone 1 is set as the highest priority function to automatically suppress other input signals;
* The equipment is equipped with abnormal work protection warning function;
* When the input signal is too large, the load is too heavy, the temperature is too high, and the line circuit, the corresponding indicator light will prompt, which has high reliability;
* 2U standard chassis design, aluminum alloy panel, beautiful and practica.

Item NO.	RS-6S120	RS-6S240	RS-6S360	RS-6S500	RS-6S650
Power Input	AC230V/50HZ				
Rated output power	120W	240W	360W	500W	650W
Voltage output	100V				
Frequency response	80Hz~18kHz +/-3dB				
Box size	485 * 88 * 300mm			485 * 88 * 343mm	
Net weight	9. 5kg			12.8kg	
Signal to Noise Ratio	＞85dB				
AC power consumption	240W	480W	720W	1000W	1300W
TH.D.(1KHz，1W)	≤0.3%				
Tone Bass	100HZ±10dB				
Treble	10KHz±10dB				
Input Sensitivity	-650mV				